
## METAL FACE






### **METAL FACE M12**









				METAL FACE		
				FLUSH	NON FLUSH	
				M12 conn	M12 conn	
NOMINAL SWITCHING DISTANCE				2 mm	4 mm	
10 20 V/J						
	NO-NC	4 wires	order No.			
	PNP			IS-12-I1-S2	IS-12-L1-S2	
10-30 Vdc NO		3 wires	order No.	95B065340	95B063871	
10 20 Vil						
10-30 Vdc NC	NC	3 wires	order No.			
40.001/1	NPN	2				
10-30 Vdc	NO	3 wires	order No.			
10.001/1	NPN	3 wires				
10-30 Vdc	NC		order No.			
10.001/1	PNP					
10-30 Vdc	NO-NC	4 wires	order No.			
10.001/1	NPN					
10-30 Vdc	NO-NC	4 wires	order No.			
10-30 Vdc	NO-NC	2 wires	order No.			
20-250 Vac/Vdc	NO	2 wires	order No.			
20-250 Vac/Vdc	NC	2 wires	order No.			
		2/3 wires				
20-250 Vac	NO		order No.			
	Analog 0-20	3 wires				
10-30 Vdc	mA		order No.			
	NAMUR	2 wires				
NAMUR amplifier			order No.			
Nominal Voltage	'		·	10-30 Vdc	10-30 Vdc	
Residual Ripple				< 10%	< 10%	
Hysteresis				< 15%	< 15%	
Max. Output Curren	t			200 mA	200 mA	
Min. Output Curren						
Residual Current				< 0,01 mA	< 0,01 mA	
Voltage Drop				< 1,5 V (I=100mA)	< 1,5 V (I=100mA)	
Operation Led				Present	Present	
Switching Frequen	су			2000 Hz	1000 Hz	
Start Up Delay	•					
Repeatability				< 1%	< 1%	
Short Circuit Prote	ction			Present (self-resetting)	Present (self-resetting)	
Electric Protection				Against polarity reversal inductive loads	Against polarity reversal inductive loads	
Temperature Limit				(-25 +70 °C)	(-25 +70 °C)	
Protection Degree				IP67	(-25 +70 °C)	
Cable Length				1507	IP0/	
Cable Section						
Housing Material				 Stainless-Steel		
Active face				Stainless-Steet Stainless Steel AISI 303	Stainless-Steel Stainless Steel AISI 303	
Tightening torque				10Nm	Staintess Steet AlSi 303	
Weight - Cable Output				I UNITI	I UNITI	
Weight - Connector Output				30 g	30 g	

#### **3 WIRES SENSORS**

#### 3 Wires Pnp Or Npn, No Or Nc







CONTACTS CONFIGURATION					
Available	Contacts numbers				
Available	1	2	3	4	
(NO or NC)	+		-	NO/NC	

#### **4 WIRES SENSORS**

#### 4 Wires (No+Nc)






# 2 0 0 0 4

CONTACTS CONFIGURATION					
Outmut	Contacts numbers				
Output	1	2	3	4	
NO + NC	+	NC	_	NO	

#### 4 Wires (Pnp/Npn, No/Nc)



CONTACTS CONFIGURATION					
Outnut	Contacts numbers				
Output	1	2	3	4	
NPN NO	+	NO	_	_	
NPN NC	-	NC	+	_	
PNP NO	+	+	-	NO	
PNP NC	_	+	+	NC	



Rev. 13, 12/2020